

EXIDEcare

1800 103 5454

www.exidereachout.com

INSTANT BRIGHTNESS SUPER PRICE

New



36 MONTH
WARRANTY*

Specifications: Capacity: 12Volt, 150Ah at C20 rating

EXIDE INSTA BRITE

Presenting Exide Instabrite. The latest offering from Exide that promises superior power backup at a fantastic price. With Exide Instabrite, you can be sure that there will be no shortage of power in your home. Get instant brightness with the best. Get Exide Instabrite.

- Unique features and superior technology: Advanced Hybrid Technology that is best suited to withstand high temperatures as well as thick plate construction with special paste formulation. Special hybrid alloy system leading to low water loss and dual plate separation (PE+GM) that reduces the possibility of premature failure
- Easy maintenance: Float/float guide to indicate electrolyte level
- Easy handling/spill-proof: Moulded handles to ensure easy handling. Top vented lid with anti-splash guards fitted with coin flush vent plugs
- Fume and leak resistant: Spark arrestor fitted in float to restrict fumes and acid during operation. Clean top with no surface leakage
- Ready for commissioning: Batteries supplied in factory-charged condition

TECHNICAL SPECIFICATIONS

Battery Type	Part Number	Ref. C ₂₀ Capacity (Ah)	Maximum Overall Dimension (mm)				Nominal Filled Weight (kg)	Electrolyte Volume (litre)	Charging Current (A)	Acid level Indicator	Battery Layout
			L	W	H	H (with float)					
IB1500	FIBO-IB1500	150	508	222	257	264	41	11	10.5	Not present	

Technical specifications are different for Bihar and UP region.

APPLICATION CHART

Electrical Load (With respect to Max. Inverter Rating)		Max. Inverter Rating	System Voltage	Recommended Battery for Different Back-Up Time		
Load Details	Wattage			5 Hrs.	3 Hrs.	2 Hrs.
1 Fan + 3 Tube Lights	200W	300VA	12V	INSBRT1500 / IB1500 /	-	-
2 Fans + 2 Tube Lights	240W	350VA		INSBRT1500 / IB1500 /	-	-
2 Fans + 3 Tube Lights	280W	400VA		-	INSBRT1500 / IB1500 /	-
3 Fans + 4 Tube Lights	400W	650VA		-	-	INSBRT1500 / IB1500 /
4 Fans + 4 Tube Lights	480W	800VA		-	-	INSBRT1500 / IB1500
6 Fans + 8 Tube Lights	800W	1300VA	24V	-	-	2S-INSBRT1500 / 2S-IB1500
8 Fans + 8 Tube Lights	960W	1600VA		-	-	2S-INSBRT1500 / 2S-IB1500

Note:

1. Cut-off voltage of inverter should be 10.5V (minimum). Tube light is considered as 40W and ceiling fan as (size 48") 70W.
2. There should be a periodic bench-charging of the battery after every three months from the date of installation
3. 2S—Two batteries connected in series

Authorised Dealer

This catalogue is issued to provide outline information only and is not deemed to form part of an offer or contract. Our policy is one of continuous improvement and we reserve the right to change details without prior notice.



EXIDE/INSTABRITE/4/2015