



THE MOST ADVANCED INTELLIGENT & SMART HOME UPS RANGE



- ▶ Most Intelligent & Smart LCD UPS with Micro Computer Inside
- ▶ Intelli Pure Sinewave Output safest for sensitive appliances along-with noiseless performance
- ▶ 5 Stage Intelligent Battery Charging Algorithm

- ▶ Best Performance with all types of Batteries, Local, Flat Plate & Tubular
- ▶ High Charging for Fast Charging for High Power-Cut areas
- ▶ Standard Charging option for Normal Power-Cut areas

SMART LCD DISPLAY

DISPLAYS FOLLOWING

- Battery Charging Time
- Backup Time
- Load Running Status


TECHNICAL SPECIFICATIONS

LUXE LCD SINEWAVE UPS				
Product	1000/12V SW	1200/12V SW	1400/12V SW	1900/24V SW
Input Voltage	Inverter Mode: 100V-300V UPS Mode: 180V-260V			
Output Voltage	Mains Mode: Same as Input / UPS Mode: 210V±10%:			
Output Frequency	UPS Mode: 50HZ ± 0.1HZ			
Switching	Automatic (from Mains to UPS and from UPS to Mains)			
Output Waveform	Mains Mode: Same as Input / UPS Mode: Pure Sinewave			
Batt. Charging Current	Constant Charging approx. 10% of the rated Battery Current in AH:			
Charger	Power Factor Controlled Boost Technology			
Efficiency	> 80%:			
UPS Overload	110%:			
UPS Short Circuit	300%			
UPS Transfer Time	≤15msec.			
Browns Out Mains Vol.	100 ± 40V			
Technology	Micro Computer Based intelligent Control Design			
Auto Reset Feature	Yes			
Operating Temp.	0°C~ 45°C			

NOTE: *Power Factor may vary depending upon the Load. * Because of a policy of continuous product improvement, specifications are subject to change without notice.



ADVANCED RESETTABLE CIRCUIT BREAKER
 Total Safety of connected Appliances



UPS & INVERTER MODE
 For Running IT & Home Load



HIGH & STANDARD CHARGING OPTION
 For Quick Battery Charging



COMPATIBLE WITH ALL BATTERY TYPES
 Tubular, Local & Flat Plate



FAN/LIGHT



LED TV



LAPTOP



WIFI-ROUTER

DISPLAYS SAFETY ALERTS WITH BUZZER

• OVERLOAD • OVERTEMPERATURE • SHORT CIRCUIT • TRIP IN THE CIRCUIT